# Easyl0<sup>®</sup>

Specification:

## EasyIO Wi-Fi Controller 14 points EasyIO-FW-14



The EasyIO-FW-14 is a new breed, high performance, freely programmable, wireless Wi-Fi Sedona controller. It has never been easier to extend your BMS because of its wireless possibilities. You will save on labor and wiring. The EasyIO-FW-14 is a perfect fit for vertical markets such as schools and retail, to have extended IO for the F-series controllers, without any downtime during installation as the network can be wireless. It's ideal for all kind of applications such as fan coils, AHU's, room and stand-alone applications, featuring SOX, TCOM, FGP2P and BACnet communication protocols.

The EasyIO-FW-14 can be programmed and live commissioned via free CPT Tools and an integrated HMTL5 dashboard. It has BACnet IP server / client, BACnet MSTP client (combination of BACnet MSTP client and BACnet IP client up to five devices total) and two Ethernet ports for daisy chain connection wiring. Wired and wireless deployment is encouraged, so there is no need to worry about IT. The EasyIO-FW-14 includes 8 UI (voltage and resistance), 4 x AO (Voltage) and 2 x DO with 24VAC volt free contact relays. For floating control, the optional FR-02 module is available to add to the FW-14.

## Power Supply Consumption 500 mA Operating temp Storage temp Operating humidity Dimensions Material Weight 410g Inputs & Outputs: Universal Input 8xUI Digital output Analog Output 4xAO 12-Bit DAC

#### Communication:

Physical Interface 1 (Port 1) BACnet Baud Rate:

WiFi Ethernet Ethernet/WiFi Support Application Support 24VAC +/- 5% or 24V DC +20%/-15% 500 mA 0 to 65 °C (32 to 150 °F) -20 to 65 °C (-4 to 150 °F) 10% to 70% relative humidity non-condensing 191 x 104 x 44 mm (L x W x H) UL Approved Plastic

12-Bit ADC (with PGA) Voltage: 0 ~ 10V DC (+/- 0,05V) Resistance input: 500 ohms to 500K ohms (+/-10 Ohm) Thermistor Sensor: 10K, 10K Shunt, 20K, 1K Balco, 1K Platinum: All (+/- 0.1 °C) UI as DI: Voltage Free Contact 2xDO (with LED's for status) Pilot duty: 24VAC, 2.0A 24VDC, 2.0A Type: Relay Contacts, SPST NO, 48VA at 24VAC 4xAO 12-Bit DAC Voltage: 0~10V, Min Impedance 10k Ohm

EIA-485 Two-wire, Half Duplex


Speed: (9.6K, 19.2k, 38.4K), Data Bit: (8 bits), Parity: (None) WIFI (802.11b/g/n) 2 Ethernet Ports 10/100M IP, TCP, UDP, ICMP, HTTP, FTP Sedona, BACnet MSTP Client, BACnet IP Server/Client and Tcom

All specifications subject to change without notice or liability to provide changes to prior purchasers, information and specifications published here are current as of the date of publication of this document. EasyIO reserves the right to change or modify specifications without prior notice. The latest product specifications can be found by contacting us. EasyIO Holdings Pte Ltd. E info@easyio.com W www.easyio.com - EasyIO Europe B.V. E info@easyio.eu W www.easyio.eu


# Easyl0<sup>®</sup>

## EasyIO Wi-Fi Controller 14 points EasyIO-FW-14





### Wiring Diagram



The FW-14 comes with one standard RS485 driver to support BACnet MSTP Client. The FW-14 also comes with two Ethernet Ports to program the Sedona Application, TCOM, FGP2P, BACnet and for web configurations.

The concept behind the FW series is that the FW-14 is a free programmable controller that perfectly fits in a network of controllers, or standalone because if its own real-time clock. The available resources inside the controller are not limited to the 14 I/O so you will be surprised by its high power.

#### Features:

- First EasyIO controller based on Wi-Fi Technology
- 8 UI
- 4 AO (voltage)
- 2 Relay DO
- 1 RS485
- 2 Ethernet 10/100 BaseT port
- Support Wifi 802.11 b/g/n
- Support Sedona VM
- Support SOX, TCOM, FGP2P
- BACnet Client IP / MSTP (5 devices)
- BACnet IP server
- SQLite (10 tables x 20 columns x 500 records)
- Email
- Dashboard (Freeboard)



CE

All specifications subject to change without notice or liability to provide changes to prior purchasers, information and specifications published here are current as of the date of publication of this document. EasyIO reserves the right to change or modify specifications without prior notice. The latest product specifications can be found by contacting us. **EasyIO Holdings Pte Ltd.** E info@easyio.com W www.easyio.com - **EasyIO Europe B.V.** E info@easyio.eu W www.easyio.eu

# Easyl0<sup>®</sup>

EasyIO Wi-Fi Controller 14 points EasyIO-FW-14



### Optional antenna's

There are two optional Wi-Fi antenna's for the EasyIO FW-series. They can extend the Wi-Fi signal of an FW controller, if it's, for example, mounted inside a panel.

• EIO-FW-ANT-1

Single 3dBi antenna with cable and magnetic base

• EIO-FW-ANT-2

Double 3dBi antenna with cable and magnetic base





All specifications subject to change without notice or liability to provide changes to prior purchasers, information and specifications published here are current as of the date of publication of this document. EasyIO reserves the right to change or modify specifications without prior notice. The latest product specifications can be found by contacting us. **EasyIO Holdings Pte Ltd.** E info@easyio.com W www.easyio.com - **EasyIO Europe B.V.** E info@easyio.eu W www.easyio.eu